

取り付け

LANmark-6A UTP

コネクタは、特別な工具を必要とせず、簡単で信頼性の高い取り付けが可能です。24個入りの箱には、詳細な取り付け説明書が同梱されています。

保証

LANmark-10G

パッチコードおよびスタガードパッチパネルと組み合わせて使用した場合、LANmark-6A UTP

ケーブルおよび接続は、25年間のクラスEAチャンネル保証を受けることができます。

Freq in MHz	Attn in dB	NEXT in dB	PSNEXT in dB	ACR-F in dB	PS ACR-F in dB	PS ANEXT in dB	PS AACR-F in dB	RL in dB
1	2.3	65.0	62.0	63.3	60.3	67.0	64.7	19.0
4	4.2	63.0	60.5	51.2	48.2	67.0	64.7	19.0
10	6.5	56.6	54.0	43.3	40.3	67.0	57.0	19.0
16	8.2	53.2	50.6	39.2	36.2	67.0	52.9	18.0
20	9.2	51.6	49.0	37.2	34.2	67.0	51.0	17.5
31,25	11.5	48.4	45.7	33.4	30.4	65.1	47.1	16.5
62,5	16.4	43.4	40.6	27.3	24.3	62.0	41.1	14.0
100	20.9	39.9	37.1	23.3	20.3	60.0	37.0	12.0
155	26.3	36.7	33.8	19.5	16.5	57.1	33.2	10.1
200	30.1	34.8	31.9	17.2	14.2	55.5	31.0	9.0
250	33.9	33.1	30.2	15.3	12.3	54.0	29.0	8.0
300	37.4	31.7	28.8	13.7	10.7	52.8	27.5	7.2
500	49.3	27.9	24.8	9.3	6.3	49.5	23.0	6.0

Product list

	Aginode ref.	Country ref.	名前
☐	N420.216	-	LANmark-6A キーストーンコネクタ カテゴリ6A 非スクリーン

☎ = Make to order, ☐ = In Stock

All drawings, designs, specifications, plans and particulars of weights, size and dimensions contained in the technical or commercial documentation of Aginode is indicative only and shall not be binding on Aginode or be treated as constituting a representation on the part of Aginode.