

Outlets: @XS-Quad

@XS-QUAD PIGTAILS 1XSC/APC

Aginode Ref: 13200970

- Up to **4 SC adapters**
- Wall mounted, on flush box or DIN rail
- No lid-opening to fix the outlet
- **Ready-to-fix** kit in option

Optical terminal outlets, installed in the subscriber's home, are the optical equipments materializing the demarcation between the FTTH operator network and the local subscriber's network.

Compact and ergonomic, its design has been studied in **partnership with SismoDesign agency** for a sober, discreet and elegant depiction, to fit at best at the inhabitant.

For security, adapters include an **automatic laser and dust protection**, called « internal shutter ».

The front side contains all the necessary indications (from top to bottom):

- Swiveling flap to protect and hide the identification label
- Area to stick Identification Label (under the flap)
- 4-colour identification code for the adapters
- Indication that polarizing slot is upwards
- Integrated laser symbol

The @XS-Quad outlets range comes in 2 families:

- The “equipped” outlet is provided with adapters and pigtails preinstalled. It must then be connected with the subscriber's cable.
- The “kit” outlet is provided pre-cabled, ready to be fastened without any outlet opening. Cable type and length are customizable.



STANDARDS

Aginode specification

@XS-Quad Pigtails 1xSC/APC

Characteristics

Construction characteristics

Colour	White RAL 9010
Material	Thermoplastic

Dimensional characteristics

Cable Diameter, range	2...5 mm
Depth	25 mm
Height	80 mm
Maximum number of adaptators	4
Splice number	4
Width	80 mm

Mechanical characteristics

IK Rating	5
-----------	---

Usage characteristics

Adaptor	SC/APC
Fire resistant	UL 94 V0
Minimum static operating bending radius	15 mm
Operating temperature, range	-5...45 °C
Packaging	Paper bag
U.V resistance	Yes
Watertightness	IP 50

ドキュメンテーション

Installation @XS-Quad pdf — 2.69 MB [ダウンロード ↓](#)

ESERV_PTOCablesStd_EN_1.xlsx xlsx — 10.27 KB [ダウンロード ↓](#)

販売および配送情報

Delivered with: 1 SC/APC pigtail + 1 SC/APC adapter + shutters for the 3 unused adapter ports

All drawings, designs, specifications, plans and particulars of weights, size and dimensions contained in the technical or commercial documentation of Aginode is indicative only and shall not be binding on Aginode or be treated as constituting a representation on the part of Aginode.