

# LANmark-OF Female Plug&Play MTP-LC Module

- Plug&Play module with 12 LC or 24 LC connections
- Available in LANmark-OF OM4 multimode and LANmark-OF OS2 singlemode
- Ultra low loss optical performance for multimode and low loss for singlemode
- Module can be easily mounted into Aginode' Plug&Play patch panel
- High density: 4 modules fit into 1U
- Straight or crossed wiring
- Plug&Play modules are pre-installed and 100 % factory tested

The Plug&Play system consists of 3 subcomponents: the Plug&Play modules, the MTP-MTP\* Pre-Terms and the Plug&Play patch panel.

The central component is the pre-installed Plug&Play module. The MTP connector at the back of the module connects at once 12 fibres to the MTP-MTP Pre-Term. Inside the module the fibres are spread out towards the LC adaptors at the front.

Up to 4 Plug&Play modules can be installed quickly into the Plug&Play patch panel with push rivets. With these 4 modules a medium density of 48 LC or a high density of 96 LC connections within 1U can be achieved.

The insertion loss for the Plug&Play module is measured according to standard IEC 61300-3-45. The minimum return loss for a MTP connection is measured according to IEC 61300-3-6.

The modules are available with a straight and a crossed wiring.

For polarity methods A,B and C of standard TIA-568-C following modules and trunks need to be used:

- For a polarity method A implementation with a method A Pre-Term straight modules are used on both sides of the link.
- For a polarity method B implementation with a method B Pre-Term a straight cassette is used on one side of the link and a



## STANDARDS

ISO/IEC 11801

crossed module on the other side of the link.

- For a polarity method C implementation with a method C Pre-Term straight modules are used on both sides of the link.

The Plug&Play module has standard unpinned (female) connectors. This matches perfectly with the pinned (male) connectors of the MTP-MTP Pre-Term.

Since all connectivity is factory terminated and tested installation times are short facilitating a quick deployment.

\* MTP is a trade name of US Conec

# LANmark-OF Female Plug&Play MTP-LC Module

## CHARACTERISTICS

### 구조적 특성

|                  |              |
|------------------|--------------|
| Connector type   | LC           |
| Fiber optic type | 멀티 모드 50/125 |
| Wiring type      | 직통           |

### 치수

|                          |    |
|--------------------------|----|
| Number of optical fibres | 24 |
|--------------------------|----|

## Product list

| Aginode ref.     | Country ref. | 이름   | Connector type | Fiber optic type | Wiring type | Number of optical fibres |
|------------------|--------------|--|----------------|------------------|-------------|--------------------------|
| ☎ N441.5L24LCVFS | -            | LANmark-OF 플러그 앤 플레이 초저손실 모듈 암형 스트레이트 24 LC OM4 바이올렛               | LC             | 멀티 모드 50/125     | 직통          | 24                       |
| ☎ N441.5L12LCVFS | -            | LANmark-OF 플러그 앤 플레이 초저손실 모듈 암형 스트레이트 12 LC OM4 바이올렛               | LC             | 멀티 모드 50/125     | 직통          | 12                       |
| ☎ N441.5L12LC0FS | -            | LANmark-OF Plug&Play Low Loss Module Female Straight 12 LC SM Blue | LC             | 싱글 모드 9/125      | 직통          | 12                       |
| ☎ N441.5L24LC0FS | -            | LANmark-OF Plug&Play Low Loss Module Female Straight 24 LC SM Blue | LC             | 싱글 모드 9/125      | 직통          | 24                       |
| ☎ N441.5L12LCVFC | -            | LANmark-OF 플러그 앤 플레이 초저손실 모듈 암 크로스형 12 LC OM4 바이올렛                 | LC             | 멀티 모드 50/125     | 교차          | 12                       |
| ☎ N441.5L24LCVFC | -            | LANmark-OF 플러그 앤 플레이 초저손실 모듈 암 크로스형 24 LC OM4 바이올렛                 | LC             | 멀티 모드 50/125     | 교차          | 24                       |
| ☎ N441.5L12LC0FC | -            | LANmark-OF Plug&Play Low Loss Module Female Crossed 12 LC SM Blue  | LC             | 싱글 모드 9/125      | 교차          | 12                       |
| ☎ N441.5L24LC0FC | -            | LANmark-OF Plug&Play Low Loss Module Female Crossed 24 LC SM Blue  | LC             | 싱글 모드 9/125      | 교차          | 24                       |

☎ = Make to order, 📦 = In Stock