

Electrical performance LANmark-6A FFTP cable

Freq in MHz	Attn in dB Max.	NEXT in dB		PSNEXT in dB		ACR-F in dB		PS ACR-F in dB		PS ANEXT in dB		PS AACR-F in dB		RL in dB	
		Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.	Min.	Typ.
1	2.1	74.3	104.3	72.3	102.3	67.8	92.8	64.8	89.8	67.0	90.0	67.0	76.7	20.0	26.0
4	3.8	65.3	95.3	63.3	93.3	55.8	80.8	52.8	77.8	67.0	90.0	66.2	75.9	23.0	26.0
10	5.9	59.3	89.3	57.3	87.3	47.8	72.8	44.8	69.8	67.0	87.0	58.2	67.9	25.0	28.0
16	7.5	56.2	86.2	54.2	84.2	43.7	68.7	40.7	65.7	67.0	85.0	54.1	63.8	25.0	28.0
20	8.4	54.8	84.8	52.8	82.8	41.8	66.8	38.8	63.8	67.0	84.0	52.2	61.9	25.0	28.0
31.25	10.5	51.9	81.9	49.9	79.9	37.9	62.9	34.9	59.9	67.0	82.1	48.3	58.0	23.6	26.0
62.5	15.0	47.4	77.4	45.4	75.4	31.9	56.9	28.9	53.9	65.6	79.0	42.3	52.0	21.5	25.0
100	19.1	44.3	74.3	42.3	72.3	27.8	52.8	24.8	49.8	62.5	77.0	38.2	47.9	20.1	24.0
155	24.1	41.4	71.4	39.4	69.4	24.0	49.0	21.0	46.0	59.6	74.1	34.4	44.1	18.8	23.0
250	31.1	38.3	68.3	36.3	66.3	19.8	44.8	16.8	41.8	56.5	71.0	30.2	39.9	17.3	22.0
300	34.3	37.1	67.1	35.1	65.1	18.3	43.3	15.3	40.3	55.3	69.8	28.7	38.4	16.8	20.0
500	45.3	33.8	63.8	31.8	61.8	13.8	38.8	10.8	35.8	52.0	66.5	24.2	33.9	15.2	20.0