

LANmark-OF ENSPACE MPO-LC 模块

LANMARK-OF ENSPACE BASE8 卡座, MPO 转 8 LC, 通用极性, 多模 OM4, 水绿色, 内置防尘盖

Aginode Ref: NSPACE.MULC8AS8

- ENSPACE Base8 卡盒前部有 8 个 LC 多模 Aqua 适配器, 后部有 1 个 MPO 适配器
- 卡盒内 MPO-8LC 光纤组件满足低损耗性能等级
- 默认极性为通用极性
- 卡盒可轻松安装到安捷诺的 ENSPACE Base8 配线架中
- 卡盒可从配线架前方和后方安装

ENSPACE Base8 MPO 卡盒前端有 8 个 LC 适配器, 后端有一个 MPO 适配器。内部的光纤组件连接 LC 适配器和 MPO 适配器。

LC 适配器的套管由高品质陶瓷套筒制成, 集成防尘门在 LC 适配器中。

卡盒可从 ENSPACE 配线架的后部和前部安装到托盘, 提高了安装、移动、添加和更改的灵活性。

最多可将 18 个 ENSPACE Base8 MPO 卡盒快速安装到 ENSPACE Base8 UHD 1U 配线架中。通过这 18 个卡盒, 可在 1U 内实现 144 LC 的超高密度。

光纤标签印在 ENSPACE 卡盒的封面上。

对于标准 TIA-568.3-E 的极性方法

A、B、C 和 U, 需要使用以下卡盒和预端接光缆:

- 对于极性方式 A, 使用 A 极性预端接光缆, 在链路两侧使用直通极性卡盒。
- 对于极性方式 B, 使用 B 极性预端接光缆, 在链路的一侧使用直通极性卡盒, 在链路的另一侧使用交叉极性卡盒。
- 对于极性方式 C, 使用 C 极性预端接光缆, 在链路两侧使用直通极性卡盒。
- 对于极性方式 U, 使用 B 极性预端接光缆, 在链路两侧使用通用极性卡盒。

ENSPACE 模块具有标准的无导针 (母头) 连接器。这与 ENSPACE MPO 预端接的 MPO 连接器的带导针 (公头) 连接器完全匹配。

模块的插入损耗根据 IEC 61300-3-45 测量, 模块的最小回波损耗根据 IEC 61300-3-6 测量。

由于所有连接都已在工厂端接和测试, 因此安装时间短, 便于快速部署。



STANDARDS

ISO/IEC 11801

LANmark-OF ENSPACE Base8 卡座, MPO 转 8 LC, 通用极性, 多模 OM4, 水绿色,内置防尘盖

Characteristics

结构特性

颜色	水绿
光纤类型	多模
布线类型	直通

传输特性

最大插入损耗, dB	0.35 dB
插入损耗, 典型值	0.2 dB
最小回波损耗, dB	20 dB

All drawings, designs, specifications, plans and particulars of weights, size and dimensions contained in the technical or commercial documentation of Aginode is indicative only and shall not be binding on Aginode or be treated as constituting a representation on the part of Aginode.

