

Outlets: @XS-Quad

@XS-QUAD PIGTAILS 4XSC/APC

Aginode Ref: 10272954

- Up to **4 SC adapters**
- Wall mounted, on flush box or DIN rail
- No lid-opening to fix the outlet
- **Ready-to-fix** kit in option

Optical terminal outlets, installed in the subscriber's home, are the optical equipments materializing the demarcation between the FTTH operator network and the local subscriber's network.

Compact and ergonomic, its design has been studied in **partnership with SismoDesign agency** for a sober, discreet and elegant depiction, to fit at best at the inhabitant.

For security, adapters include an **automatic laser and dust protection**, called « internal shutter ».

The front side contains all the necessary indications (from top to bottom):

- Swiveling flap to protect and hide the identification label
- Area to stick Identification Label (under the flap)
- 4-colour identification code for the adapters
- Indication that polarizing slot is upwards
- Integrated laser symbol

The @XS-Quad outlets range comes in 2 families:

- The “equipped” outlet is provided with adapters and pigtails preinstalled. It must then be connected with the subscriber's cable.
- The “kit” outlet is provided pre-cabled, ready to be fastened without any outlet opening. Cable type and length are customizable.



STANDARDS

Aginode specification
Orange/France Telecom

@XS-Quad Pigtails 4xSC/APC

Characteristics

구조적 특성

색상	하얀색 RAL 9010
Material	Thermoplastic

치수

Depth	25 mm
Height	80 mm
Width	80 mm
Cable Diameter, range	2...5 mm
Splice number	4
Maximum number of adaptators	4

기계적 특성

IK Rating	5
-----------	---

사용 특성

操作温度范围	-5...45 °C
Adaptor	SC/APC
Fire resistant	UL 94 V0
Minimum static operating bending radius	15 mm
U.V resistance	Yes
Packaging	Plastic bag
Watertightness	IP 50

문서

Installation @XS-Quad pdf — 2.69 MB [다운로드 ↓](#)

ESERV_PTOCablesStd_EN_1.xlsx xlsx — 10.27 KB [다운로드 ↓](#)

판매 및 배송 정보

Delivered with: 4 SC/APC pigtails + 4 SC/APC adaptors

All drawings, designs, specifications, plans and particulars of weights, size and dimensions contained in the technical or commercial documentation of Aginode is indicative only and shall not be binding on Aginode or be treated as constituting a representation on the part of Aginode.